



iMedia HID Bluetooth Remote - Configuration Instructions

Reference the Quick Start Guide on the iMedia HID Bluetooth Remote product page for button map.

- To configure the iMedia remote Hold B1 and B4 on power up to power up the iMedia remote in SPP mode to allow remote configuration. The iMedia remote can be configured via Bluetooth, using an Android, Windows, or OSX device (can't be configured with an iOS device).
- 2. Once in cmd mode: with SB,0,<number>, that will select button set 0,1,2, or 3 which corresponds to set mode 1,2,3, or 4
- 3. You can change the buttons with SB, <button number>, <value>
- 4. You can check the current set with "B"

Another feature "t" allows you to embed multiple buttons pressed at the same time. So for example the number '1' is 0x1E and number '2' is 0x1F if you want to send a 1 and then a 2 you would use SB1,001E,001F. Now, if you want to send a 1 and a 2 TOGETHER you use SB1,401E,001F the "4" bit at the top says to take all the keys and send them all at the same time.